

EZ View : 4Ch Real-time DVR *Plug & Secure!*

SHR-1041K **NEW**



Features

- Simple & Easy Installation
- Easy Backup (USB 2.0) & Easy User Interface
- Easy Connectivity with Any Monitor & TV (VGA, Composite)
- Dynamic Quad View: Single, Quad, Sequence

- Motion Detection
- Functional Cameras: Weather Resistant & Night Vision
- Eco-Friendly Compliance (ROHS)
- User Friendly Web Viewer

Dimensions (unit:mm)



Specifications

Model	SHR-1041K	
Video Input	4 Camera Inputs (RJ11 4EA, BNC 4EA)	
Video Output	1 Composite Video Output(BNC), 1 VGA Main Monitor Output	
Audio	MIC 4 Inputs (RJ11), 1 Output (RCA)	
Main Display	120CIF/sec(NTSC), 100CIF/sec(PAL) 1/4/Sequential	
Motion Detection	10 step sensitivity	
Alarm Input	4 Alarm Inputs(RJ11)	
Alarm Output	1 Alarm Outputs(Relay), Normally Open or Normally Closed Programmable	
PTZ	1 RS-485	
User Interface	English, French, and Spanish GUI with full mouse operation Keypad, Remote controller	
Recording	MEPG-4(half-pel motion vector), G.711(64Kbps) NTSC : Max 120FPS(CIF), 60FPS(Half D1), 30FPS(D1) PAL : Max 100FPS(CIF), 50FPS(Half D1), 25FPS(D1) Channel independent recording setup for resolution, frame rate and quality Mode : Simple, Advanced(Manual, Motion, Alarm, Schedule, Panic) Schedule : 24 different recording configuration is possible in a day Various Video Quality (Highest/ High/ Standard/ Low) Pre-recording (max 5 sec)	
Play Back	Search mode : Calendar/Timeline, Event/Log x1, x2, x4, x8, x16, x32, x64 1 / 4 multi screen playback	
Performance	Triplex (Playback, Recording, Network)	
Archiving	USB interfaced storage, Watermark	
Time	GMT time zone, Auto DST, NTP support	
System	Embedded Linux, Watch dog, Abnormal shutdown detection System auto recovery User group : admin, manager, guest F/W upgrade : USB	
Network	RJ45, 10/100Mbps Up to 4 connection simultaneously DHCP, DDNS Bandwidth Management	
Remote Client	Web Viewer	
Storage	1 SATA up to 2 terabyte of internal storage Format / Write once / Overwriting	
Event	Sensor / Motion / Video Loss / HDD failure Triggers recording, alarm out, e-mail notification, buzzer, video popup or log	
Interface	1 High speed USB2.0 port (front) 1 RJ-45, 1 RS-485, 1 PS/2	
Power	DC 12V / 4A Adaptor	
Operating Temperature	0°C ~ 40°C (32°F ~ 104°F)	
Dimension	280mm(W) x 305mm(D) x 60mm(H)	
Camera Cable Length	100ft Guaranteed	Light Sensor Auto Switching IR LED Control